

## Audio Transformer

# **PC** Mount

## TY-141P

#### **Description:**

These transformers operate in the 200 Hz to 15,000 Hz range, making them suitable for a broad application spectrum in the audio industry. These devices are used in line matching, telephone coupling, pulse trigger, driver, interstage, output, isolation and input applications.

10000Ω CT

10000Ω CT

100mW

4 mA

**Operating Temperature Range:** -20° C to 85° C

#### Electrical Specifications at 25° C:

- Primary Impedance: 1.
- Secondary Impedance: 2.
- Output: 3.
- Primary DC Unbalance: 4.
- 5. Frequency Response:
- Impedance Matching: 6.
- Longitudinal Balance 7.
- Insertion Loss @ 1K Hz: 8.
- Return Loss: 9.
- 10. Total Harmonic Distortion
- 11. DCR:
  - Primary (1-3)
  - Secondary (4-6)
- 12. Turns Ratio:
- 13. Dielectric Strength

#### + 2dB from 200 to 15,000 Hz 10% over full frequency range > 45dB < 1.5dB > 26dB < 0.5% between 275Hz and 3.5KHz 820Ω□□ Nominal□□ 1070Ω Nominal 1:1 1500V Pri to Sec to Core


### **Construction:**

Bobbin has plug-in terminals which are spaced to provide fixed mounting centers. Pins are rugged, minimizing the incidence of bent pins from handling.

## **Outline Dimensions:**

- A. Dimensions: As figures show B. PIN DIM. : .042" x .020"
- C. Weight. : 0.51 oz.

### Schematic:



RoHS Compliance: As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.

\*Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics website for the most current version. For soldering and washing information please see http://www.triadmagnetics.com/fag.html

	Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757	460 Harley Knox Blvd. Perris, California 92571	Publish Date: May 31, 2019
--	---	---	----------------------------



