

POWER TRANSFORMER Chassis Mount: International Series

VPL28-1700

Electrical Specifications (@25C)

- 1. Maximum Power: 50.0VA
- 2. Input Voltage **Series**: 230VAC @ 50/60Hz, **Parallel**: 115VAC@ 50/60Hz
- 3. Output Voltage Series1: 28V CT@ 1.786A, Parallel2: 14V @ 3.572A
- 4. Voltage Regulation: 20% TYP @ full load to no load
- 5. Hipot: 3500VAC between primary to secondary and windings to core.
- 6. Recommended Fuse3:

Series: Littelfuse p/n 313 2HXP, 2.0A 250V, slow blow, $\frac{1}{4}$ x 1 $\frac{1}{4}$ or, Cooper Bussmann p/n BK/MDL-2, 2.A 250V, $\frac{1}{4}$ x 1 $\frac{1}{4}$ Parallel: Littelfuse p/n 313 4HXP, 4.0A 250V, slow blow, $\frac{1}{4}$ x 1 $\frac{1}{4}$ or,

Cooper Bussmann p/n BK/MDL-4, 4A 250V, 1/4 x 1 1/4



Dual winding construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements. Shrouds are provided over the connections of the leads to the windings on both primary and secondary coils. Devices are designed with a minimum of 6mm creepage distance between the primary and secondary and are manufactured with a Class B (130°C) insulation system.

Agency Files:

UL File: E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3 cUL: File E65390, For Canadian Use (CSA 22.2, No.66.1-06 and No.66.3-06) TUV: File R72182067, EN 61558-1:2005+A1, EN61558-2-6:2009. Double Insulated. Non-inherently Short-Circuit-Proof.







Dimensions:			Units: In inches		
Α	В	С	D	Е	F
2.562	4.00	2.250	3.562	8.00	0.187

Weight: 2.3 lbs.

Connections4:

Transformer is provided with 8" (203mm) long, 0.25" (6mm) stripped and tinned, stranded 18 AWG, UL 1015 lead wire.

Input: Series - BLK to BLU, Jumper WHT to BRN

Parallel - BLK to BLU, Jumper BLK to BRN and WHT to BLU

Output: Series - RED to GRY, Jumper YEL to VIO

Parallel - RED to GRY, Jumper RED to VIO and YEL to GRY

RoHS Compliance: As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.


* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


² Non-Inherently limited. Class 2 not wet, Class 3 wet.


³ Fuse must be used on **secondary** as conditions of acceptability for UL Class2/3 operation.

⁴ Primary and secondary windings are designed to be connected in series or parallel. Windings are not intended to be used independently.









SCHEMATIC

Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris. California 92571

Publish Date: April 26, 2023

¹ Non-Inherently limited. Class 3.